

## DETAIL LEGEND:


- ① FX LUMINAIRE EX TRANSFORMER. MOUNT TO WALL WITH STAINLESS STEEL SCREWS.
- ② GFI PROTECTED 120V POWER WITH WATERPROOF OUTLET COVER
- ③ INSTALL LOW VOLTAGE CABLES INSIDE 1.5" [4 CM] DIA. GRAY PVC CONDUIT UNTIL CABLE IS 12" [30 CM] BELOW FINISHED GRADE.
- ④ FINISHED GRADE
- ⑤ TRANSFORMER POWER CABLE AND PLUG

### FX LUMINAIRE

1940 Diamond Street  
San Marcos, CA 92078  
Main: 760-744-5240  
Technical Support: 760-591-7383  
www.fxI.com

## NOTES:

- A. FX LUMINAIRE EX TRANSFORMER. SEE LIGHTING PLAN FOR WATTAGE, SIZE AND SWITCHING TYPE.
- B. ALL METAL PARTS MUST BE GROUNDED IN ACCORDANCE TO NEC GUIDELINES.
- C. BOTTOM OF TRANSFORMER CABINET TO BE A MINIMUM OF 12" [30 CM] ABOVE FINISHED GRADE.
- D. MOUNT BEHIND PLANT MATERIAL OR BOULDERS TO OBSCURE A DIRECT VIEW OF THE TRANSFORMER. LOCATE AWAY FROM SPRAY OF IRRIGATION HEADS.
- E. ALWAYS REFER TO FX PRODUCT INSTALLATION NOTES PRIOR TO INSTALLATION.
- F. UNIT EMITS A HUM. DO NOT MOUNT ON EXTERIOR BEDROOM OR OFFICE WALLS.



## EX MOUNTING BRACKET WALL MOUNT



FXLuminaire.

NOT TO SCALE